



Main

Range of product	INF32 INF40 INF100...160 INF200...800 INF63
Range	Fupact
Device short name	Auxiliary contact
Product or component type	Auxiliary contact
Device application	Connection
Range compatibility	Fupact - Fupact INF fuse-switch disconnecter
Signal contacts composition	1 NC

Complementary

Auxiliary contacts type	Standard
Mounting mode	Left hand side
[Ith] conventional free air thermal current	16 A
[Ie] rated operational current	DC-12 : 2 A DC 48 V DC-12 : 6 A DC 24 V DC-12 : 0.4 A DC 250 V AC-15 : 6 A AC 50/60 Hz 24 V AC-15 : 6 A AC 50/60 Hz 48 V AC-15 : 2 A AC 50/60 Hz 660/690 V DC-12 : 0.1 A DC 440 V AC-15 : 6 A AC 50/60 Hz 220/240 V AC-15 : 3 A AC 50/60 Hz 440 V DC-12 : 0.1 A DC 380/415 V AC-15 : 6 A AC 50/60 Hz 250 V AC-15 : 4 A AC 50/60 Hz 380/415 V AC-15 : 6 A AC 50/60 Hz 110 V DC-12 : 1.1 A DC 110 V DC-12 : 0.4 A DC 220/240 V
Minimum load	10 mA at 24 V

Contractual warranty

Warranty period	18 months
-----------------	-----------

49610