



Main

| | |
|-----------------------------|--|
| Range of product | INF100...160 |
| Range | Fupact |
| Device short name | Blown fuse indicator |
| Product or component type | Blown Fuse Indicator |
| Device application | Display |
| Range compatibility | Fupact - Fupact INF fuse-switch disconnecter |
| Poles description | 3P 4P |
| Signal contacts composition | 1 NC 1 NO |

Complementary

| | |
|--|--|
| [I _{th}] conventional free air thermal current | 16 A |
| [I _e] rated operational current | DC-12 : 2 A DC 48 V DC-12 : 6 A DC 24 V DC-12 : 0.4 A DC 250 V AC-15 : 6 A AC 50/60 Hz 24 V AC-15 : 6 A AC 50/60 Hz 48 V AC-15 : 2 A AC 50/60 Hz 660/690 V DC-12 : 0.1 A DC 440 V AC-15 : 6 A AC 50/60 Hz 220/240 V AC-15 : 3 A AC 50/60 Hz 440 V DC-12 : 0.1 A DC 380/415 V AC-15 : 6 A AC 50/60 Hz 250 V AC-15 : 4 A AC 50/60 Hz 380/415 V AC-15 : 6 A AC 50/60 Hz 110 V DC-12 : 1.1 A DC 110 V DC-12 : 0.4 A DC 220/240 V |
| Minimum load | 10 mA at 24 V |

Contractual warranty

| | |
|-----------------|-----------|
| Warranty period | 18 months |
|-----------------|-----------|

49634

